

500W Digital Mixer Amplifier

Features

- With built-in Bluetooth, FM and USB function
- With 3 MIC IN, 1 EMC IN, 2 AUX IN, 1 AUX OUT
- Can be controlled by the infrared remote controller
- With segment code tube screen, and intuitive display, more convenient for users to use
- Support 100V and 70V constant voltage output, and 4Ω~16Ω constant resistance output
- With priority function, and the priority is MUTE>EMC=Alarm=Chime>MIC1>Others



Model	DMA650U
MIC1 IN Sensitivity	10mV ±1mv
MIC2 IN Sensitivity	10mV±1mv
AUX1 IN Sensitivity	350mV±50mv
AUX2 IN Sensitivity	350mV±50mv
EMC IN Sensitivity	350mV±50mv
MIC Frequency Response	120Hz?12kHz (±3dB)
AUX Frequency Response	80Hz?15kHz (±3dB)
Distortion	<1%
Treble	10dB (±2)
Bass	10dB (±2)
Rated Output Power	AC110-240V
Gross Weight	7.8 KG
Net Weight	6.3KG
Package Dimension	550×500×165mm
Maximum Package Dimension	610×390×240mm (4PCS)
Gross Weight	3 KG
Net Weight	3.7Kg (1pc)

Exclusive Distributon in Bangladesh

