

### FIRE ALARM CONTROL PANEL INFINITY 8-IN2



#### Features

- Optional add-on zonal sounder circuits (50mA Max.)
- Auxiliary supply (29 Volts, 250mA)
- Zonal to common timer (when fitted with zonal sounder boards)

Mains Voltage	230V AC +10% / -15% @ 50/60 Hz
System Voltage	24V DC (Nominal)
Zone Voltage	21V DC (Nominal)
Sounder Alarm Output	2 x 150mA @ 24V DC
Fault Relay	1 x Volt Free Relay, SELV @ 1A Max
Zone Capacity	32 devices per zone
Remote sounder operation	Via N/O contact connected to Class Change
Sounder Activation Delay	0 to 10 minutes in 1 minute increments
Zone End of line	1N4002 Diode (Cathode Stripe to Zone +ve)
Sounder End of Line	10K resistor
Charger Voltage	27.6V
Battery cut off	Battery voltage less than 20V
Battery Internal Resistance limit	0.9 ohm
Enclosure size	371 x 302 x 93 (mm)
Weight	3 kg (Excluding Batteries)
Maximum battery space	2 x 3.4 Ah, 12 Vdc sealed lead acid

**Exclusive Distributon in Bangladesh**

