

**120W Mini Digital
Mixer Amplifier**



Features

- Support infrared remote control.
- Speaker output of 100V or 70V & 4 -16 Ω .
- 2 MIC inputs, 2 EMC inputs, 2 line inputs, 1 line output.

Model	MP120UB
Power Supply	~110V-240V/50/60Hz
MIC1 input sensitivity	8mV $\pm$ 1mV
MIC2 input sensitivity	8mV $\pm$ 1mV
AUX1 input sensitivity	360mV $\pm$ 20mV
AUX2 input sensitivity	360mV $\pm$ 20mV
EMC input sensitivity	360mV $\pm$ 20mV
MIC frequency response	180Hz?10kHz? $\pm$ 3dB?
AUX frequency response	70Hz?16kHz? $\pm$ 3dB?
Noise	<5mV (4? load output port)
Distortion	<1% 1KHz
Treble adjustment	10dB? $\pm$ 2?
Bass adjustment	10dB? $\pm$ 2?
Rated power supply	AC220V
Speaker outputs	35W 4?, AC220V
Interface output voltage	70V, 100V (Constant voltage output)
Machine size(L $\times$ W $\times$ H)	247*198*66mm
Packing size	343*302*121mm (1PC)
Net Weight	2.6kg
Gross Weight	3.25Kg
Net Weight	2.5Kg

Exclusive Distributon in Bangladesh

