

**250W Mini Digital Mixer Amplifier
with USB & Bluetooth**

Features



- Support IR remote control.
- Built-in Bluetooth, radio and USB function.
- 2 MIC IN, 2 EMC IN, 2 LINE IN, 1 LINE OUT.
- With priority function, priority is EMC/MIC1>AUX1/AUX2/MIC2.
- 100V or 70V constant voltage output,
4Ω~16 Ω constant resistance output.

Model	MP250UB
Rated power	250W
MIC1 input sensitivity	8mV±10%
MIC2 input sensitivity	8mV±10%
MIC input sensitivity	8mV±10%
AUX1 input sensitivity	350mV±10%
AUX2 input sensitivity	350mV±10%
EMC IN sensitivity	350mV±10%
MIC Frequency Response	200Hz?10kHz?±3dB?
AUX Frequency Response	100Hz?16kHz?±3dB?
Noise	<10mV
Distortion	<1% 1KHz
Interface Output Voltage	70V,100V(Constant voltage output)
Treble adjustment	10dB?±2?
Machine Dimension(D×W×H)	250×230×66mm
Package Dimension	363×292×106mm (1PC)
Maximum Package Dimension	610×390×240mm (4PCS)
Gross Weight	3 KG
Net Weight	3.7Kg (1pc)

Exclusive Distributon in Bangladesh

